

## MA-240UF

### Public Address System 240W Mixer Amplifier with Mp3 & FM



#### Description:

The Public Address (PA) 240 Watts Mixer Amplifier with Mp3 & FM is suitable for school, super market, bank, hotel BGM and speech use.

It integrates pre amplifier, Mp3 player, FM tuner and mixer power amplifier into one 19" 2U height unit of tabletop design, which is economy but of high reliable performance.

The tabletop mixer amplifier rated power out at 240W. Its speaker outputs with 100V, 70V and 4-16 Ohms for versatile connections.

It integrates three microphone and two line inputs. Mic1 VOX with priority. Microphone1 on front panel by phone jack, microphone2-3 on rear panel by phone jack, line 1-2 on rear panel by RCA inputs. Microphone1-3 & Line1-2 inputs volume control on front panel with bass and treble tone control.

The amplifier is design with complete protection of overload, short circuit and high temp to avoid any damage.

#### Features:

- ✓ Public address (PA) tabletop mixer power amplifier.
- ✓ Commercial & industrial range BGM & paging amplifier.
- ✓ Mixer amplifier with Mp3 player by USB input.
- ✓ Built-in FM tuner with FM antenna on rear panel
- ✓ Rated power output of 240W.
- ✓ 70V, 100V and low impedance 4-16 Ohms speaker outputs.
- ✓ 3 microphone inputs and 2 line inputs.
- ✓ Mic1 on front panel by phone jack, mic2-3 on rear panel by phone jack.
- ✓ Line 1-2 inputs on rear panel by RCA.
- ✓ Microphone1 of VOX features of highest input priority.
- ✓ Microphone1-3 & Line1-2 inputs volume control on front panel with bass and treble tone control.
- ✓ Power and output level meters.
- ✓ Overload, short circuit and high temp protection.
- ✓ With natural cooling fan to control the internal temperature.

# MA-240UF

## Public Address System 240W Mixer Amplifier with Mp3 & FM

### Rear Panel:



### Specification:

<b>Model</b>	MA-240UF
<b>Description</b>	Public Address System 240W Mixer Amplifier with Mp3 & FM
<b>Rated Power Output</b>	240W RMS
<b>Built-in Sources</b>	Mp3 player by USB on front panel FM tuner
<b>Speaker Output</b>	70V, 100V and 4-16Ω
<b>Input</b>	Mic1-3: 600 ohms(Ω) 5-8 mV, unbalanced, Line1-2: 10k ohms(Ω) 150-470 mV, unbalanced
<b>Frequency Response</b>	60-15KHz
<b>THD</b>	<0.5% at 1kHz, 1/3 rated power
<b>S/N Ratio</b>	Line: 85 dB , MIC: >72 dB
<b>Protection</b>	High temp, short circuit, overload protection
<b>Power Supply</b>	AC230V or AC110V, 50-60Hz
<b>Power Consumption</b>	350W
<b>Dimension</b>	484(W)×350(D)×88(H)mm
<b>Packaging:</b>	520(W)×435(D)×185(H)mm
<b>Net. Weight</b>	13.8kg
<b>Gross Weight</b>	15.4kg